

HIKOKI

Cordless

SB3608DA(H4Z)

36V Brushless Belt Sander



MEV
MULTI VOLT
**BRUSH
LESS**
Brushless Motor
Li-ion

Features

- 5-stage variable speed dial to match the sanding level to the applications
- Auto Mode changes the speed depending on the load, lowering vibration and noise during no-load operation.
- Tool free quick belt change system
- Sanding belt tracking system allows the sand paper belt to protrude 1.5 - 3.0mm past the end of the pulleys to get tight against an edge
- Efficient dust collection with easy to attach dust bag or vacuum swivel attachment to help keep the work space clean
- Compatible with the HiKOKI Multi Volt battery

Specifications

Battery Voltage	36V
Motor type	Brushless
Switch type	Trigger switch
Variable Speed Control	Yes, 5 speeds plus automode
Sanding Belt Size	76 x 533mm
No-load belt speed	122 - 450m/min
Braking function	Yes
Soft start	Yes
Overload protection	Yes
Overheat protection	Yes
Restart prevention function	Yes
Belt-changing system	Tool-free(lever)
Belt-changing system	Tool-free
Dust bag position	Left
Weight(including the battery)	4.2kg
Dimensions L x W x H	323 x 150 x 199mm
Battery	HiKOKI MultiVolt battery