BS 18 LTX BL Q I (602359850) Cordless drill driver

Order No. 602359850
EAN 4061792188211



Representative picture

- A true power house: safe, brushless drill driver with maximum power for the toughest applications
- Metabo quick system: quick exchange of chucks, bit holders, angle adapters and more for flexible work
- Selectable "impuls" mode for removal of stubborn screws and for spot-drilling on smooth surfaces
- Spindle with magnetic hexagon recess for screwdriver bits for working without chuck
- Precision Stop: electronic torque control with increased precision for accurate and intricate working
- Variable speed, forward and reverse rotation and quick stop for versatile use in wood and metal
- Overload protection: protects the motor from overheating
- Euro collar (Ø 43 mm) for versatile use
- Electronic safety shutdown: no kickback if the drill bit stops unexpectedly - for high user safety
- Integrated LED work light with afterglow function for optimal brightness in the work area
- With handy belt hook and bit case which can be fixed either on the right or left side
- Many brands, one battery pack system: This product can be combined with all 18V battery packs and chargers of the CAS brands: www.cordless-alliance-systems.com

Technical values

KEY FIGURES

Maximum torque, soft	65 Nm / 575 ft. lbs
Pulse torque	65 Nm / 575 in-lbs
Maximum torque, hard	130 Nm / 1151 ft. lbs
Adjustable torque	1 - 20 Nm // 9 - 177 in-lbs

Drill Ø steel	13 mm / 1/2 " "
Drill-Ø soft wood	68 mm / 2.68 " "
No-load speeds	0 - 550 / 0 - 2000 rpm
Chuck capacity	1.5 - 13 mm // 1/16 - 1/2 "
Collar diameter	43 mm / 1 11/16 "
Weight without battery pack	1.7 kg / 3.7 lbs
Weight with battery pack	2.1 kg / 4.6 lbs

VIBRATION

Drilling in metal	2.2 m/s^2
Uncertainty of measurement K	1.5 m/s^2

NOISE EMISSION

Sound pressure level	79 dB(A)
Sound power level (LwA)	87 dB(A)
Uncertainty of measurement K	5 dB(A)

Scope of delivery

- Quick-change chuck
- Quick-change bit holder "Quick"
- Side handle
- Belt hook and bit case
- without battery pack, without charger